



## Control and power.

Combining precision control with ample power, this professional grade processor stores macros and commands to deliver complete control over your connected smart home.

The ProLink.r processor is PC programmable with the wizard-based **Pro Control Studio** software, and communicates with the Pro24.r and iPro.8 remotes via one-way 433 MHz RF signal.

Four integrated IR routing ports offer adjustable output strength and four IR Emitters are included in the ProLink.r Plus. Its two voltage-sensing inputs enable improved management of connected devices.

For additional control flexibility, the ProLink.r provides one-way LAN control via iPad® and iPhone® with an activated ProPanel app from the App Store.®



Four (4) IR Emitters included.



### SPECIFICATIONS

Supported remote control	Pro24.r and iPro.8
Support for iPad®, iPhone®, iPod touch® app	Yes LAN (1-way)
Support for virtual PC control	Yes LAN (1-way)
Integrated RS-232 ports	N/A
Ethernet control	Yes LAN (1-way only)
Ethernet for programming	Yes
Adjustable IR output strength	Yes
Integrated IR routing ports	4
IR emitters included	4
Voltage sense inputs	2
Integrated RF control	1-way (433 MHz)
System commands and macro storage	Unlimited (Determined by available memory)
Integrated antenna	Yes
USB programming	Yes
Dimensions H x W x D	4.1" x 6.62" x 1.28" (104.1mm x 168.1mm x 32.5mm)
Warranty	3 years (parts & labor)